

HOLLAND 1 LIGHT SMALL PENDANT

SKU# 012020, 012021.

Rated Voltage 220-240V~ 50Hz.

To ensure correct function and safety, please read and follow all instructions carefully before assembly, installation and use of this product. Please keep instructions for future reference.

Warranty

- This luminaire is covered by a 12-month warranty. The warranty is from date of purchase, not the date of installation.
- If the luminaire is not assembled and installed by a licensed electrician, the warranty will be void.
- Please retain the proof of purchase and evidence of installation by a licensed electrician for any warranty enquiries.
- Warranty will be void if there is any damage due to improper usage or modification to the luminaire.
- Failure to comply with instructions in this manual may increase the risk of damage or injury and will void the warranty.

Installation Requirements

- This luminaire must be assembled and installed by a licensed electrician.
- All wiring and installation of the luminaire must adhere to the latest local and national wiring rules.
e.g. AS/NZS 3000 Electrical Installations.
- This luminaire is a Class I product and must be earthed during wiring and installation.
- Do not exceed the maximum wattage rating.
- Select a suitable location for installation:
 - This luminaire is suitable for use in indoor environments only.
 - The mounting point must support 2 times the weight of the luminaire.
 - If installing the luminaire in an area prone to moisture, ensure that the area is well ventilated, and an appropriately rated exhaust fan is used if required. Damage or corrosion caused by environmental exposure (including salt air, high humidity, moisture or condensation) is not a product fault, and as such is not covered under warranty.
- Take care not to pull any electrical wires during unpacking as this may damage the connection.
- Lay out all the components on a smooth surface and make sure no components are missing, or have been damaged during transport, before assembling. Do not operate/install any luminaire which appears damaged in any way. If parts are missing or damaged, return the complete luminaire to the place of purchase for inspection, repair or replacement.
- Ensure power to the circuit you are working on has been switched OFF before commencing any electrical work.

Installation Directions

NOTE: Assembly and installation of this luminaire must be done by a licensed electrician.

WARNING: Ensure power to the circuit you are working on has been switched OFF before commencing any electrical work.

1. Remove all packaging material from the product and be careful not to throw away accessories that may be hidden within the packaging material. If assembly is required, place the luminaire on a smooth non-scratch surface.
2. Determine the required length of the suspension cord (H) for your installation. If adjustment is required, loosen the cord anchorage (G), set the suspension cord (H) to the desired length, and then re-tighten the cord anchorage (G).

NOTE: Take care not to overtighten the screw on the cord anchorage (G), as it may damage the cord (H).


3. Remove the mounting bracket (B) from the canopy (F) by loosening the screws (E) on the sides.
4. Use the mounting bracket (B) as a template to mark the screw hole positions on the ceiling.
5. Depending on the mounting surface, determine if anchors (A) or mounting accessories are required for installation. If they are required, ensure they are suitable for the mounting surface and the surrounding environment.
6. Install the mounting bracket (B) onto the ceiling by using appropriately sized mounting screws (C). Ensure the screws (C) used are suitable for the mounting surface and the surrounding environment.
7. Connect the mains supply wire to the terminal block (D).

Mains Supply Wire	Luminaire Wire / Terminal block
Earth – Yellow/Green	Yellow/Green or 
Neutral – Blue or Black	Blue or N
Live – Brown or Red	Brown or L

8. Ensure the wires are secure, and no bare wires are exposed.
- NOTE: The luminaire is a Class I product and must be earthed during wiring and installation.**
9. Install the canopy (F) back onto the mounting bracket (B) and secure by tightening the screws (E) on the sides.
 10. Slide and re-position the decorative cover (I) onto the top of the lamp holder (J).
 11. Remove the lamp holder ring (L) from the lamp holder (J).
 12. Install the shade (K) onto the lamp holder (J) and secure by installing the lamp holder ring (L) back onto the lamp holder (J).
 13. Install a lamp (M - not included) into the lamp holder (J). Do not exceed the maximum wattage rating.
 14. After the installation is fully completed, switch on the luminaire to test and enjoy your new lighting product.

RELAMPING

1. Ensure the power is turned OFF to the luminaire and the lamp is fully cooled down before relamping.
2. Lift up the decorative cover to hold the luminaire and suspension cord to prevent it from rotating or twisting.
3. Remove the old lamp by twisting it anti-clockwise and install a new lamp by twisting it clockwise until it is secure.



Safety Tips

- Always ensure the power is OFF and the luminaire has cooled down before performing any maintenance, cleaning, changing the globes or making any adjustment to the luminaire.
- To avoid injury or damage to the luminaire, ensure that power leads and screws are secure before connecting power
- Select a suitable location away from liquids and hazards.
- To clean wipe with a soft damp cloth. Do NOT soak or immerse the luminaire in water or other liquids.
- Ensure that the luminaire does not come in contact with corrosive chemicals/solvents or abrasive cleaners etc.

Specifications

SKU #	012020	012021
Colour	Beige with Natural Travertine	Bronze Finish with Brown Marble
Rated Voltage	220-240V~ 50Hz	
Rated Wattage	45W Max.	
Lamp Holder	ES / E27	
Weight	1.2kg	
Canopy Dimensions	H:35mm Dia:120mm	
Luminaire Dimensions	H:168mm Dia:245mm Suspension: 2000mm MAX	