

SEASIDE TALIS WALL BRACKET

SKU# 238030,238031

Rated Voltage 220-240V~ 50Hz

To ensure correct function and safety, please read and follow all instructions carefully before assembly, installation and use of this product. Please keep instructions for future reference.

Warranty

- This luminaire is covered by a 5-year warranty. The warranty is from date of purchase, not the date of installation.
- If the luminaire is not assembled and installed by a licensed electrician, the warranty will be void.
- Please retain proof of purchase and evidence of installation by a licensed electrician for any warranty claims.
- Warranty will be void if there is any damage due to improper usage or modification to the luminaire.
- Failure to comply with the instructions in this manual may increase the risk of damage or injury and will void the warranty.

Installation Requirements

- This luminaire must be assembled and installed by a licensed electrician.
- All wiring and installation of the luminaire must adhere to the latest local and national wiring rules. e.g. AS/NZS 3000 Electrical installations.
- This luminaire is a Class I product and must be earthed during wiring and installation.
- This luminaire is rated IP65, this must be maintained during wiring and installation.
- Do not exceed the maximum wattage rating.
- Select a suitable location for installation:
 - The mounting point must be able to support 2 times the weight of the luminaire.
 - This luminaire is protected against water penetration to IP65 standards, which is against low-pressure jets of water from all practicable directions. This must be maintained during wiring and installation
- Take care not to pull any electrical wires during unpacking as this may damage the connection.
- Lay out all the components on a smooth surface and make sure there are no components missing before assembling. If parts are missing, return the complete product to the place of purchase for inspection or replacement.
- Check whether the luminaire has been damaged during transport. Do not operate/install any product which appears damaged in any way. Return the complete product to the place of purchase for inspection, repair or replacement.
- Ensure power to the circuit you are working on has been switched OFF before commencing any electrical work.

Installation Directions

1. Remove all packaging material from the product and be careful not to throw away accessories that may be hidden within the packaging material.
2. Remove the mounting bracket (D) from the luminaire (G) by loosening locking screws (I) and locking washers (H) using the Allen key (J) provided.
3. Use the mounting bracket (D) as a template to mark the screw positions on the wall.
4. Install the mounting bracket (D) onto the wall by using appropriately sized mounting screws (F), washers (E) and anchors (C). Ensure the screws (F), washers (E) and anchors (C) used are suitable for the mounting surface and the surrounding environment.
5. Connect the mains supply wire to the terminal block(A). Ensure the wires are secure and no bare wires are exposed.

Mains Supply Wire

Earth – Yellow/Green 

Neutral – Blue or Black

Live – Brown or Red

Luminaire Wire/ Terminal Block

Yellow/Green or 

Blue or N

Brown or L

NOTE: This luminaire is a Class I product and must be earthed during wiring and installation.

NOTE: Ensure both the luminaire and mounting bracket earth wire is connected to the earth terminal block (A).


6. Connect the terminal pins (B) of the luminaire (G) into the terminal block (A) on the mounting bracket (D).
7. Secure the luminaire (G) onto the mounting bracket (D) using the locking screws (I) and locking washers (H) with the Allen key (J) provided.

NOTE: Ensure washers (E) and locking washers (H) are used while installation to maintain IP65 rating.

8. Install a globe (K– Not included) into the lamp holder of luminaire (G). Do not exceed the maximum wattage rating.
9. After installing the globe (K- not included), attach the shade (L) onto the luminaire (G) by rotating clockwise until firmly secured.
10. After the full assembly and installation, switch on the luminaire to test and enjoy your new lighting product.

RELAMPING:

1. Switch OFF the power supply at the mains and allow the luminaire to cool completely before replacing the globe.
2. Carefully remove the shade (L) by rotating it anticlockwise until it is released from the luminaire (G).
3. Remove the existing globe and install a new globe (K- not included) of the correct type and wattage. Do not exceed the maximum wattage rating.
4. Refit the shade (L) by rotating it clockwise until it is secured firmly.
5. Restore power and switch on the luminaire to ensure correct operation.



Safety Tips

- Always ensure the power is OFF and the luminaire has cooled down before performing any maintenance, cleaning, changing the globe or making any adjustment to the luminaire.
- To avoid injury or damage to the luminaire, ensure that power leads and screws are secure before connecting the power.
- The luminaire must not be used if the shade has been cracked. Replace any cracked protective shield before using the luminaire.
- Select a suitable location away from liquids and hazards.
- Ensure that the luminaire does not come in contact with corrosive chemicals/solvents or abrasive cleaners etc.
- To clean, wipe with a damp clean cloth. Do NOT soak or immerse the product in water or other liquids.

Specifications

SKU #	238030	238031
Colour	Aged Solid Bronze	Nickel
Rated Voltage	220-240V~ 50Hz	
Rated Wattage	15W Max (LED only)	
Lamp Holder	ES/E27	
IP Rating	IP65	
Weight	2.2Kg	
Dimensions	H:320mm W:180mm E:320mm	